

Upgrading Boxer 30 to Boxer 4K30

These instructions explain how to upgrade from Boxer 30 to Boxer 4K30.

Required hardware

The following hardware is required to upgrade to Boxer 4K30.

- Boxer 30 to Boxer 4K30 Upgrade kit (144-118101-XX), which includes:
 - 1 x HBMIC card (High Bandwidth Multi input card)
 - 1 x Boxer 4K documentation
- Computer running Christie Twist v2.3 or above
- License file (.key) provided by Christie Technical Support
The license file (.key) is only valid for the Boxer 30 unit serial number(s) specified at the time of order.

Upgrading the projector

The upgrade license is added to the projector using the Christie Twist v2.3 or higher application.

1. Before proceeding, confirm the serial number of the projector matches the unit(s) specified on your purchase order.
2. Unzip the license file (.key) to a known location on your computer.
3. Power on the Boxer 30 projector.
4. Ensure the software version is 1.4.0 or higher.
If necessary, upgrade to the latest software.
5. Connect both the Boxer 30 projector and the computer running Christie Twist to the same network using Ethernet.
6. From the Start menu of the Christie Twist computer, select **Christie > Twist 2.x > Christie Projector License Utility**.
7. In the Christie Projector License Utility dialog, click **Browse**.
8. Navigate to the location of the unzipped license file (.key), supplied by Christie Technical Support, and select it.
9. From the Projectors list, select the projector you want to apply the upgrade to.

10. To upgrade the projector, click **Apply**.
11. Reboot the projector.
12. Install the HBMIC option card.
13. Repeat steps 3 to 12 for each additional projector.

Technical support

Technical support for Christie products is available at:

- North and South America: +1-800-221-8025 or Support.Americas@christiedigital.com
- Europe, Middle East, and Africa: +44 (0) 1189 778111 or Support.EMEA@christiedigital.com
- Asia Pacific: +65 6877-8737 or Support.APAC@christiedigital.com